



## SH 6000 E UK

PORTABLE POWER

50Hz UK range Technic

### Product advantages

- ➔ Solid and compact frame
- ➔ Electric start
- ➔ Large Autonomy Fuel Tank
- ➔ OHV Honda professional engine
- ➔ Oil level safety

### Divers

Exceptional long run time suited to professional working conditions.



This product is QUALIGEN certified. Defined by the SIMOTHERM and GIGREL professional organisations, the QUALIGEN charter is intended to provide a label for equipment compliant with current regulations (user safety, noise level, power, sales information, After Sales Service) in order to provide the highest level of quality of our and thus to guarantee the users safety.

## SH 6000 E UK

### General specifications

Range	Technic
Frequency (Hz)	50
Max. power (kW)	6
Max power. (kVA)	6.6
Nominal voltage (V)	230
Number of phase	Single phase - 230V
Acoustic pressure level Lw(A)	97
Noise level dB(A) - 1m	
Noise level dB(A) - 7m	68

### Engine specifications

Engine trademark	Honda
Engine type	GX 390
Distribution	O.H.V.
Start	Electrical
Fuel	Petrol (unlead)
Autonomy (h)	8
Consumption (L/h)	2.5
Tank (L)	20
Oil Guard	Yes
Capacity (cm <sup>3</sup> )	389
Oil capacity (L)	1.1

### Alternator specifications

Type	Without collar or brush
Regulation	Mechanical
Protection class	IP 23
Insulation class	H

### Plugs and panel descriptive

1 x 2P+T 115V 16A - Thermal Breaker + 1 x 2P+T 115V 32A - Thermal Breaker + 1 x 2P+T 230V 16A - Thermal Breaker + 1 x 2P+T 230V 32A - Thermal Breaker

### Dimensions and weight

Lenght (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kgs)	87

### Packaging

Packaging type	Box
Length (cm)	78.5
Width (cm)	58
Height (cm)	59.5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	200

## Options



R05A	<b>Automatic mains failure panel R05A</b>	Automatic start, remote control, start on dry contact.
R05A	<b>Automatic mains failure panel R05A</b>	Automatic start, remote control, start on dry contact.
R07	<b>Trolley kit R07</b>	Trolley kit for generating sets > 3 kW with a stretcher system for easy handling.
R19	<b>Maintenance kit for HONDA engines R19</b>	10 maintenance kits for Honda GX270 and GX390 engine (except SH 4000, Alizé 6000E et Alizé 7500 TE)
R50	<b>Male plugs 230V/16A R50</b>	16A blue 230V male plug - Sold per 1 or 10
R51	<b>Male plugs 115V/16A R51</b>	16A yellow 115V male plug - Sold per 1 or 10
R52	<b>Male plugs 230V/32A R52</b>	32A blue 230V male plug - Sold per 1 or 5
R53	<b>Male plugs 115V/32A R53</b>	32A yellow 115V male plug - Sold per 1 or 5
R54	<b>R54 adaptor kit</b>	Adaptator R54 16A/13A adaptor unit. Sold per 1 or 3
R55	<b>R55 adaptor kit</b>	ADAPTATOR R55 16A/13A adaptor economy. Sold per 1 or 3
R56	<b>R56 adaptor kit</b>	ADAPTATOR R56 16A/13A double adaptor. Sold per 1 or 3
RPQ		For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm <sup>2</sup> cable.